

## VL-M3

### Active Monitor Set



The VL-M3 is a highly compact active monitor set perfectly suited as an extension to computer systems, multi-track recorders, or any portable music player. It consists of two bass reflex enclosures with 3-inch full-range loudspeakers powered by a 24-watt amplifier built into the left cabinet. A stereo line input on RCA connectors is provided as well as binding terminals for the loudspeaker connection between the left and right cabinets.

The VL-M3 offers a wide frequency range from compact size and features a volume control for easy level adjustment. An AC adapter as well as line and loudspeaker cables are included.

### Main Features

- **Convenient, compact stereo powered monitor system**
- **Ideal to monitor sounds from your computer, multi-track recorder or portable music player**
- **Good-sounding components, little space required**
- **One active enclosure with 12 W + 12 W built-in amplifier, one passive enclosure**
- **3-inch full-range loudspeaker chassis**
- **Bass reflex enclosures**
- **RCA stereo line input**
- **Binding terminals for interconnection of both cabinets**
- **Volume control and power switch on rear panel**
- **Powered by AC adapter (included)**
- **Audio cable (stereo mini-jack to RCA) and loudspeaker cable included**

### Specifications

Amplifier output power	12 W + 12 W
Loudspeaker chassis	3" full-range
Enclosure	Bass reflex type
Frequency response (amplifier)	46 Hz - 20 kHz, +0/-3 dB
Frequency response (loudspeaker)	105 Hz - 20 kHz
Sensitivity	-6 dBV (0.5 Vrms)
Input connector	RCA pin jack
Input impedance	5 kOhm
Power requirements	AC adapter (Tascam PS-1818)
AC adapter input	AC 100-240V, 50/60 Hz
AC adapter output voltage	18 V DC
AC adapter output electric current	1.8 A
Power consumption	15 W
Dimensions (W x H x D)	100 mm x 152 mm x 126 mm
Weight	
Left channel active unit	1.2 kg
Right channel passive unit	1.1 kg

Design and specifications subject to change without notice.

Last modified: 2010-10-07 14:39:20 UTC

