

When Apple released the Mac OS X 10.4.10 operating system upgrade, the FireWire component that communicates with audio interfaces was changed. This affected many FireWire audio interfaces, including TASCAM's. The following procedure will downgrade that FireWire Audio component back to a pre-10.4.10 state until updated drivers become available.



## Apple FireWire Downgrade

1. Along with these instructions, you should have downloaded a file called "AppleFWAudio-2.0.1fc1-e8.pkg." Double click that file to launch the installer.
2. Follow the on-screen instructions. At the end of the installation, you will be asked to restart your computer.
3. After restarting, you can confirm that your FireWire component has been downgraded. Click on the Apple menu in the top left corner of your screen, select "About This Mac" and click the "More Info" button.



4. When System Profiler opens, click on "Software Extensions" in the left column. (It may take a few seconds to load.) Scroll down to "AppleFWAudio" and confirm that it is now version 2.0.1.

